




Triggers

zero 88



DMX In



MIDI Show Control



OSC Examples



| 1st | 2nd | 3rd |
|-----------|--------------------------|-----------------------------------|
| /zeros | /cue /q | /go /pause /next |
| /flx | | /go /pause /level |
| /lighting | /playback /pb | /level /release |
| /lx | /blackout /bo /dbo | /view |
| | /grandmaster /gm | /level <i>(can be omitted)</i> |
| | /macro | |

Go

| | String | Combined | Argument (with or without quotes) |
|--------------------------------|-------------------|-------------------|---|
| Go Playback X Cue Y | /zeros/cue/go/X/Y | /zeros/cue/go/X/Y | /zeros/cue/go "X", "Y" /zeros/cue/go "X/Y" |
| Go Cue Y (current playback) | /zeros/cue/go/Y | | /zeros/cue/go "Y" |
| Go (current playback) | /zeros/cue/go | | |

Pause

| | String | Combined | Argument (with or without quotes) |
|-----------------------------|------------------|----------|---|
| Pause (current playback) | /zeros/cue/pause | | |

Next

| | String | Combined | Argument (with or without quotes) |
|------------------------------------|---------------------|---------------------|---|
| "Next" Playback X Cue Y | /zeros/cue/next/X/Y | /zeros/cue/next/X/Y | /zeros/cue/next "X", "Y" /zeros/cue/next "X/Y" |
| "Next" Cue Y (current playback) | /zeros/cue/next/Y | | /zeros/cue/next "Y" |

Go

| | String | Combined | Argument (with or without quotes) |
|--------------------------|----------------------|----------|---|
| Go Playback X | /zeros/playback/go/X | | /zeros/playback/go "X" |
| Go (current playback) | /zeros/playback/go | | |

Pause

| | String | Combined | Argument (with or without quotes) |
|-----------------------------|-------------------------|----------|---|
| Pause Playback X | /zeros/playback/pause/X | | /zeros/playback/pause "X" |
| Pause (current playback) | /zeros/playback/pause | | |

Playback levels

| | String | Combined | Argument (with or without quotes) |
|--|--|--|---|
| Playback X to level Y% over Z seconds | /zeros/playback/level/X/Y /zeros/playback/level/X/Y/Z | /zeros/playback/level/X "Y" /zeros/playback/level/X/Y "Z" /zeros/playback/level/X "Y", "Z" /zeros/playback/level/X "Y/Z" | /zeros/playback/level "X", "Y" /zeros/playback/level "X/Y" /zeros/playback/level "X", "Y", "Z" /zeros/playback/level "X/Y/Z" |
| <i>Level in %. Optional fade time, in seconds If fade time is not set, ZerOS will use the raise/lower time ("move" rather than "fade")</i> | | | |

Release

| | String | Combined | Argument (with or without quotes) |
|-------------------------------|---------------------------|----------|---|
| Release Playback X | /zeros/playback/release/X | | /zeros/playback/release "X" |
| Release (current playback) | /zeros/playback /release | | |

View

| | String | Combined | Argument (with or without quotes) |
|-----------------|------------------------|----------|---|
| View Playback X | /zeros/playback/view/X | | /zeros/playback/view "X" |


| | String | Combined | Argument (with or without quotes) |
|---|--|---|---|
| Run User Macro X | /zeros/macro/X | | /zeros/macro "X" |
| Grand Master to level Y% over Z seconds | /zeros/grandmaster/level/Y /zeros/grandmaster/level/Y/Z /zeros/grandmaster/Y /zeros/grandmaster/Y/Z | /zeros/grandmaster/level/Y "Z" /zeros/grandmaster/Y "Z" | /zeros/grandmaster/level/ "Y" /zeros/grandmaster/level "Y", "Z" /zeros/grandmaster "Y" /zeros/grandmaster "Y", "Z" |
| Blackout | /zeros/blackout/X | | /zeros/blackout "X" |

Level in % (The word "Level" is optional within the string. It is not required but can be included to match the equivalent Playback level command). Optional fade time, in seconds


To turn Blackout on, X can = "1", "on", "enable", "enabled", or "true"

To turn Blackout off, X can = "0", "off", "disable", "disabled", or "false"

Vision.Net




CAN



| Function | iCANnet Cable Colours |
|----------|-----------------------|
| 0V | Black |
| CAN L | Blue |
| Shield | Silver |
| CAN H | White |
| +VDC | Red |



Remote Switches



| Remote Input Connector | Pin | Remote Switch |
|------------------------|-----|---------------|
| | 1 | Switch 1 |
| | 2 | Switch 2 |
| | 3 | Switch 3 |
| | 4 | Switch 4 |
| | 5 | Switch 5 |
| | 6 | Switch 6 |
| | 7 | Switch 7 |
| | 8 | Switch 8 |
| | 9 | Common |

OSC



MIDI Timecode



MIDI Notes

